

This Page Is Inserted by IFW Operations
and is not a part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,
please do not report the images to the
Image Problem Mailbox.**




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04M 3/18, H02H 9/04		A1	(11) International Publication Number: WO 96/01015
			(43) International Publication Date: 11 January 1996 (11.01.96)
(21) International Application Number: PCT/SE95/00800		(81) Designated States: CA, CN, JP, KR, US, European patent (AT, BE, CH, DE, DK, ES, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).	
(22) International Filing Date: 28 June 1995 (28.06.95)			
(30) Priority Data: 9402277-9 28 June 1994 (28.06.94) SE		Published With international search report. In English translation (filed in Swedish).	
(71) Applicant (for all designated States except US): TELEFONAKTIEBOLAGET LM ERICSSON [SE/SE]; S-126 25 Stockholm (SE).			
(72) Inventor; and			
(75) Inventor/Applicant (for US only): ERIKSSON, Hans, Oskar [SE/SE]; Aspnäsvägen 28, S-175 37 Järfälla (SE).			
(74) Agents: BOHLIN, Björn et al.; Telefonaktiebolaget LM Ericsson, Patent Dept., S-126 25 Stockholm (SE).			

(54) Title: AN APPARATUS FOR PROTECTING A SUBSCRIBER LINE INTERFACE CIRCUIT AGAINST OVERVOLTAGES

(57) Abstract

An apparatus for protecting a subscriber line interface circuit (1) against overvoltages occurring on its two input wires (A, B) and exceeding the voltage of the supply voltage source of the subscriber line interface circuit (1). A resistor (RA, RB) is connected in series with a respective input wire (A, B) to respective input terminals (LA, LB) of the subscriber line interface circuit. Each input terminal (LA, LB) is connected to the anode of a respective first diode (DA1, DB1), whose cathode is connected to the positive terminal of the supply voltage source, and also to the cathode of a respective second diode (DA2, DB2). The anodes of the second diodes are connected to the cathode of a thyristor (TAB) which is common to the second diodes. The anode of the thyristor is connected to the positive terminal of the supply voltage source and the gate of the thyristor is connected to the negative terminal of the supply voltage source.



FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AT	Austria	GB	United Kingdom	MR	Mauritania
AU	Australia	GE	Georgia	MW	Malawi
BB	Barbados	GN	Guinea	NE	Niger
BE	Belgium	GR	Greece	NL	Netherlands
BF	Burkina Faso	HU	Hungary	NO	Norway
BG	Bulgaria	IE	Ireland	NZ	New Zealand
BJ	Benin	IT	Italy	PL	Poland
BR	Brazil	JP	Japan	PT	Portugal
BY	Belarus	KE	Kenya	RO	Romania
CA	Canada	KG	Kyrgyzstan	RU	Russian Federation
CF	Central African Republic	KP	Democratic People's Republic of Korea	SD	Sudan
CG	Congo	KR	Republic of Korea	SE	Sweden
CH	Switzerland	KZ	Kazakhstan	SI	Slovenia
CI	Côte d'Ivoire	LI	Liechtenstein	SK	Slovakia
CM	Cameroon	LK	Sri Lanka	SN	Senegal
CN	China	LU	Luxembourg	TD	Chad
CS	Czechoslovakia	LV	Latvia	TG	Togo
CZ	Czech Republic	MC	Monaco	TJ	Tajikistan
DE	Germany	MD	Republic of Moldova	TT	Trinidad and Tobago
DK	Denmark	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	US	United States of America
FI	Finland	MN	Mongolia	UZ	Uzbekistan
FR	France			VN	Viet Nam
GA	Gabon				

An apparatus for protecting a subscriber line interface circuit against overvoltages

TECHNICAL FIELD

The present invention relates to apparatus for protecting a subscriber line interface circuit against overvoltages appearing on its two input wires and exceeding the voltage of the supply voltage source of the subscriber line interface circuit.

BACKGROUND ART

10 It is known to protect subscriber line interface circuits against overvoltages, primarily against overvoltages in the form of lightening-induced overvoltage pulses caused, with the aid of a so-called primary protector which may, for instance, consist in a spark gap which functions to reduce the overvoltages on the subscriber line to a voltage of about one kilovolt. A so-called secondary overvoltage protector is fitted to the subscriber line, to deal with these residual pulses of about one kilovolt. The secondary overvoltage protector may have the form of a known circuit marketed by General Semiconductor under the trademark TRANSZORB, or a circuit marketed by RCA under the trademark SURGECTOR.

Current standards require the secondary overvoltage protector to be earthed to the apparatus stand with a separate wire. However, this can create problems that are manifested in the form of residual pulses in the order of magnitude of some hundred volts across a subscriber line interface circuit connected to the subscriber line. Modern line interface boards, in which the line interface circuit is a monolithic integrated circuit, are very often broken-down by lightening, due to residual pulses from the secondary overvoltage protector appearing across the two input wires of the circuit board.

US-A 4,456,940 teaches an overvoltage protector which includes, among other things, two diodes whose anodes are each connected to a respective input terminal of a subscriber line interface circuit and whose cathodes are connected to earth, and further includes two thyristors whose cathodes are each connected to a respective input terminal on the subscriber line interface circuit and whose anodes are connected to earth. The thyristor gates are connected to the supply voltage of the subscriber line interface circuit. This protective circuit protects the subscriber line interface circuit against overvoltages. However, the thyristors are relatively space-consuming and a reduction in their number would be a significant advantage. It is sometimes necessary to match the thyristors, so that they will ignite or fire simultaneously, i.e. for the same voltage across the cathodes with equal voltage across the gate. However, the document does not describe several cascade-connected overvoltage protectors.

SUMMARY OF THE INVENTION

The object of the invention is to eliminate the effect on a subscriber line interface circuit of residual pulses that emanate from secondary overvoltage protectors.

This object is achieved with apparatus according to the invention and having the characteristic features set forth in the following Claims.

One advantage afforded by the present invention is that the number of thyristors required in the tertiary overvoltage protector has been reduced in comparison with the number required in the known protectors, therewith reducing the space required by the overvoltage protector. Another advantage is that matching between two or more thyristors to ensure that the thyristors will be activated at one and the same voltage level is no longer necessary.

BRIEF DESCRIPTION OF THE DRAWING

The invention will now be described in more detail with reference to the accompanying drawing, in which Fig. 1 is a block schematic which illustrates a primary overvoltage protector circuit, a secondary overvoltage protector circuit and a tertiary overvoltage protector circuit connected to a subscriber line interface circuit; and Fig. 2 illustrates an embodiment of a tertiary overvoltage protector circuit according to the invention for a subscriber line interface circuit.

BEST MODE OF CARRYING OUT THE INVENTION

Fig. 1 is a block schematic illustrating an inventive total overvoltage protector for a subscriber line interface circuit 1. The subscriber line interface circuit 1 has its input terminals LA and LB connected to a pair of outlet terminals 5, 6 on a tertiary overvoltage protector 2. The tertiary overvoltage protector 2 has two input terminals 7, 8 connected in cascade to two output terminals 9, 10 of a secondary overvoltage protector 3, which in turn has two input terminals 11, 12 connected in cascade to two output terminals 13, 14 of a primary overvoltage protector 4. The primary overvoltage protector 4 has two input terminals 15, 16, each of which is connected to a respective resistor RA and RB, the resistances of which are normally in the order of 10 ohms and each of which is connected to a respective input wire A and B of the subscriber line interface circuit 1. The primary overvoltage protector 4 is normally of a known kind, i.e. a spark gap, and the secondary overvoltage protector 3 is normally of a known kind, such as the kind designated TRANSZORB or SURGECTOR. As shown in the Figure, the tertiary overvoltage protector 2 and the subscriber line interface circuit 1 are connected to system earth, whereas the secondary overvoltage protector 3 is connected to apparatus earth.

Overvoltage pulses that are caused by lightening for instance, and which occur on the two input wires A and B of the circuit 1 are reduced by the primary protector 4 to residual pulses in the order of one kilovolt, these residual pulses being reduced to the order of some hundred volts by the secondary overvoltage protector. These residual pulses arriving from the secondary protector 3 and having a voltage level which exceeds the supply voltage to the subscriber line interface circuit are eliminated by the tertiary overvoltage protector 2.

10 The inventive tertiary overvoltage protector 2 is shown in broken lines in Fig. 2. The secondary and primary overvoltage protectors have been omitted from the Fig. 2 illustration, and the tertiary overvoltage protector 2 is shown connected directly to the resistors RA and RB. The input terminals LA, 15 LB of the subscriber line interface circuit 1 are each connected to the anode of a respective first diode DA1, DB1, the cathodes of which first diodes are connected to system earth. The input terminals LA and LB are also each connected to the cathode of a respective second diode DA2 and DB2, 20 wherein the anodes of the second diodes are connected to the cathode of a thyristor TAB which is common to said second diodes and the anode of which is connected to system earth and the gate of which is connected to a connection terminal on the voltage-supply source of the interface circuit 1, said supply 25 voltage source having the potential -VB. The tertiary overvoltage protector 2 thus includes the first diodes DA1 and DB1, the second diodes DA2 and DB2 and the thyristor TAB.

The subscriber line interface circuit 1 is supplied between earth and the voltage -VB, which is normally -50V. The input 30 terminals GND and VBB of the subscriber line interface circuit 1 are therefore connected to system earth and the potential -VB respectively.

Occurring overvoltages will be restricted in the following manner:

Positive overvoltages are restricted with the aid of the diodes DA1, DB1, whereas negative overvoltages are restricted to about 2V beneath -VB, in other words more negative than -VB, where 2V corresponds to the sum of the forward voltage drop of respective diodes DA2, DB2 and the forward voltage drop across the gate for turning on the thyristor TAB. The input terminals LA, LB are drawn to earth when the thyristor TAB ignites.

The inventive protective circuit is thus effective in eliminating the problem associated with the breakdown of subscriber line interface circuits that are subjected to lightening induced overvoltage pulses.

CLAIMS

1. Apparatus for protecting a subscriber line interface circuit (1) against overvoltages occurring on its two input wires (A, B) and exceeding the voltage of the supply voltage source of the subscriber line interface circuit (1), wherein a resistor (RA, RB) is connected in series with a respective input wire (A, B) to a respective input terminal (LA, LB) of the subscriber interface circuit, wherein each input terminal (LA, LB) is connected to the anode of a respective first diode (DA1, DB1), and wherein the cathodes of the first diodes are connected to the positive terminal of the supply voltage source, characterized in that each input terminal (LA, LB) is also connected to the cathode of a respective second diode (DA2, DB2); in that the anodes of said second diodes are connected to the cathode of a thyristor (TAB) which is common to the second diodes; in that the anode of the thyristor is connected to the positive terminal of the supply voltage source and the gate of said thyristor is connected to the negative terminal of said supply voltage source.
2. Apparatus for protecting a subscriber line interface circuit (1) against overvoltages that occur on its two input wires (A, B) and that exceed the voltage of the supply voltage source of said subscriber line interface circuit (1), wherein a resistor (RA, RB) is connected in series with a respective input wire (A, B) to a respective input terminal (15, 16) on a primary overvoltage protector (4) which is connected in cascade to a secondary overvoltage protector (3) which is connected in cascade to a tertiary overvoltage protector (2) which is connected in cascade to the subscriber line interface circuit, wherein the secondary overvoltage protector is connected to apparatus earth and the tertiary overvoltage protector includes a first diode (DA1, DB1) for each input wire, wherein respective input terminals (LA, LB) of the subscriber line interface circuit are connected to the anode

of respective first diodes (DA1, DB1) and wherein the cathodes of the first diodes are connected to the positive terminal of the supply voltage source, characterized in that the tertiary overvoltage protector (2) also includes a thyristor (TAB) and
5 a second diode (DA2, DB2) for each input wire (A, B), wherein respective input terminals (LA, LB) of the subscriber line interface circuit (1) are also connected to the cathode of a respective second diode (DA2, DB2), wherein the anodes of the second diodes are connected to the cathode of the thyristor,
10 the anode of which is connected to the positive terminal of the supply voltage source and the gate of which is connected to the negative terminal of the supply voltage source.




FIG. 1




FIG. 2

INTERNATIONAL SEARCH REPORT

International application No.

PCT/SE 95/00800

A. CLASSIFICATION OF SUBJECT MATTER

IPC6: H04M 3/18, H02H 9/04

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC6: H04M, H02H

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

SE,DK,FI,NO classes as above

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 4908854 A (BENGT G. LÖFMARK), 13 March 1990 (13.03.90), column 2, line 42 - line 66, figure 1 --	1-2
A	US 4377832 A (JOHN J TONEY ET AL), 22 March 1983 (22.03.83), column 2, line 37 - column 3, line 40, figures 1-2, abstract --	1-2
A	US 4456940 A (LARS E. HAMMERBERG ET AL), 26 June 1984 (26.06.84), column 2, line 26 - line 40; column 2, line 52 - column 4, line 12, figures 1,4,5, abstract --	1-2



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents:

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention.

"X" document of particular relevance: the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance: the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

5 October 1995

Date of mailing of the international search report

19 -10- 1995

Name and mailing address of the ISA/

Swedish Patent Office
Box 5055, S-102 42 STOCKHOLM
Facsimile No. +46 8 666 02 86

Authorized officer

Roland Landström
Telephone No. +46 8 782 25 00

INTERNATIONAL SEARCH REPORT

International application No.

PCT/SE 95/00800

C (Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 5003588 A (NORBERT WINGERATH), 26 March 1991 (26.03.91), figures 1-2, abstract -----	1-2

INTERNATIONAL SEARCH REPORT

Information on patent family members

28/08/95

International application No.

PCT/SE 95/00800

Patent document cited in search report		Publication date	Patent family member(s)		Publication date
US-A-	4908854	13/03/90	AU-B-	604383	13/12/90
			AU-A-	2533788	02/05/89
			CN-A-	1032610	26/04/89
			DE-A-	3868478	26/03/92
			DK-B-	168316	07/03/94
			EP-A,B-	0311580	12/04/89
			IE-B-	61777	30/11/94
			JP-T-	2501525	24/05/90
			SE-B,C-	459138	05/06/89
			SE-A-	8703890	09/04/89
			WO-A-	8903625	20/04/89
US-A-	4377832	22/03/83	NONE		
US-A-	4456940	26/06/84	AU-B-	547598	24/10/85
			AU-A-	7934082	20/07/82
			EP-A,B-	0067839	29/12/82
			SE-B,C-	426002	29/11/82
			SE-A-	8009142	24/06/82
			SU-A,A-	1258339	15/09/86
US-A-	5003588	26/03/91	WO-A-	8202287	08/07/82
			DE-A-	3781327	01/10/92
			EP-A,B-	0248319	09/12/87
			SE-T3-	0248319	